



UPGRADE



YAMAHA									
2 HP	2		1-Cyl.	84→02	B5HS	4210			0.6
	2	2A			B6HS	4510	BR6HIX	3419	0.6
	2	2B		→84	BR5HS	3722			0.6
	2	2B		85→86	B7HS	5110	BR7HIX	7067	0.6
	2	2B		87→	BR5HS	3722			0.6
	2	2C		95→	B7HS	5110	BR7HIX	7067	0.6
2.5 HP	2.5	F2.5	4-Stroke	03→05	BR6HS	3922	BR6HIX	3419	0.6
3 HP	3		1-Cyl.	88→02	B6HS-10	1052	BR6HIX	3419	1.0
	3	3A (Malta)			BR6HS-10	1090	BR6HIX	3419	1.0
4 HP	4		1-Cyl.	84→99	B7HS	5110	BR7HIX	7067	0.6
	4	F4	1-Cyl. 4-Stroke	99→05	BR6HS	3922	BR6HIX	3419	0.6
	4	F4B		10→	CR6HSB	6500	CR6HIX	7274	0.7
5 HP	5		1-Cyl.	84→02	B7HS	5110	BR7HIX	7067	0.6
	5	5C			BR7HS	4122	BR7HIX	7067	0.6
	5	5D			B5HS	4210			0.6
	5	F5A		10→	CR6HSB	6500	CR6HIX	7274	0.7
6 HP	6		2-Cyl.	86→00	B7HS-10	2129	BR7HIX	7067	1.0
	6	6A			B6HS	4510	BR6HIX	3419	0.6
	6	6B			B5HS	4210			0.6
	6	6D			BR6HS-10	1090	BR6HIX	3419	1.0
	6	F6	OHV 4-Stroke	01→05	BR6HS-10	1090	BR6HIX	3419	1.0
	6	F6C		10→	CR6HSB	6500	CR6HIX	7274	0.7
7 HP	7	7A			B6HS	4510	BR6HIX	3419	0.6
8 HP	8	8A			B6HS	4510	BR6HIX	3419	0.6
	8	8B			B7HS	5110	BR7HIX	7067	0.6
	8	8C	2-Cyl. 2-Stroke	86→05	B7HS-10	2129	BR7HIX	7067	1.0
	8	E8D			BR7HS-10	1098	BR7HIX	7067	1.0
	8	F8A		→85	CR6HS	7023	CR6HIX	7274	0.6
	8	F8A, AEM, AM		86→02	CR5HS	2874			0.6
	8	F8B, BE, BM		86→	CR5HS	2874			0.6
	8	F8C, FT8D	OHV 4-Stroke	00→05	BR6HS-10	1090	BR6HIX	3419	1.0
9 HP	9	9A			B6HS	4510	BR6HIX	3419	0.6
9.9 HP	9.9	9.9D, 9.9F Dia. 14 mm plug	2-Stroke	85→20	BR7HS-10	1098	BR7HIX	7067	1.0
	9.9	F9.9A, F9.9B Dia. 10 mm plug	4-Stroke	85→97	CR6HS	7023	CR6HIX	7274	0.6
	9.9	F9.9C Dia. 12 mm plug	4-Stroke	98→08	DPR6EA-9	5531			0.9
	9.9	F9.9F, F9.9J Dia. 14 mm plug	4-Stroke	08→21	BR6HS-10	1090	BR6HIX	3419	1.0
	9.9	F9.9H Dia. 12 mm plug	4-Stroke	09→22	DPR6EB-9	3108			0.9
	9.9	FT9.9A Dia. 10 mm plug	4-Stroke	99→99	CR6HS	7023	CR6HIX	7274	0.6



UPGRADE



MODEL	HP	ADDITIONAL INFORMATION	ENG TYPE E: = Eng no.	DATE	PART NO.	STOCK NO.	UPGRADE	STOCK NO.	GAP MM	
YAMAHA (CONTINUED)										
9.9 HP	9.9	FT9.9D Dia. 12 mm plug	4-Stroke	99→08	DPR6EA-9	5531			0.9	
	9.9	FT9.9G, FT9.9L Dia. 14 mm plug	4-Stroke	08→21	BR6HS-10	1090	BR6HIX	3419	1.0	
12 HP	12	12A			B7HS	5110	BR7HIX	7067	0.6	
13 HP	13	13.5A			BR7HS-10	1098	BR7HIX	7067	1.0	
13.5 HP	13.5	13.5F			B7HS-10	2129	BR7HIX	7067	1.0	
	13.5	F13.5A			DPR6EA-9	5531			0.9	
15 HP	15	15, 15A Dia. 14 mm plug	2-Stroke	84→05	B7HS-10	2129	BR7HIX	7067	1.0	
	15	15B, 15C			B7HS	5110	BR7HIX	7067	0.6	
	15	15D, 15F		95→	BR7HS-10	1098	BR7HIX	7067	1.0	
	15	F15A Dia. 12 mm plug		98→04	DPR6EA-9	5531			0.9	
20 HP	20	20A, 20B			B6HS	4510	BR6HIX	3419	0.6	
	20	20C, 20CE, 20CM	2-Cyl.	96→97	B7HS-10	2129	BR7HIX	7067	1.0	
	20	20D			BR7HS-10	1098	BR7HIX	7067	1.0	
	20	C20	2-Cyl.	96→	BR7HS	4122	BR7HIX	7067	0.6	
	20	F20A			DPR6EA-9	5531			0.9	
25 HP	25	25B	3-Cyl. 2-Stroke	94→95	BR8HS-10	1134	BR8HIX	7001	1.0	
	25	25B	2-Cyl. 2-Stroke	01→10	BR7HS-10	1098	BR7HIX	7067	1.0	
	25	25D, 25DE	2-Cyl. 2-Stroke	85→01	BR7HS	4122	BR7HIX	7067	0.7	
	25	25J	3-Cyl. 2-Stroke	87→99	BR7HS-10	1098	BR7HIX	7067	1.0	
	25	25N	2-Cyl. 2-Stroke	88→16	BR7HS-10	1098	BR7HIX	7067	1.0	
	25	25Q	3-Cyl. 2-Stroke	90→94	BR8HS-10	1134	BR8HIX	7001	1.0	
	25	25V	2-Cyl. 2-Stroke	96→01	BR7HS-10	1098	BR7HIX	7067	1.0	
	25	E25A, E25B	2-Cyl. 2-Stroke	98→03	BR7HS-10	1098	BR7HIX	7067	1.0	
	25	F25A	2-Cyl. 4-Stroke	98→09	DPR6EA-9	5531			0.9	
	25	F25D, F25G	2-Cyl. 4-Stroke	09→21	DPR6EB-9	3108			0.9	
	25	FT25B	2-Cyl. 4-Stroke	00→09	DPR6EA-9	5531			0.9	
	25	FT25F	2-Cyl. 4-Stroke	09→22	DPR6EB-9	3108			0.9	
28 HP	28	28A, 28AE		87→97	B7HS-10	2129	BR7HIX	7067	1.0	
30 HP	30	30A, 30AE, 30AM		84→86	B7HS	5110	BR7HIX	7067	0.6	
	30	30D		87→02	B7HS-10	2129	BR7HIX	7067	1.0	
	30	30G, 30H		95→	B8HS-10	5126	BR8HIX	7001	1.0	
	30	C30	2-Cyl.	89→92	B7HS	5110	BR7HIX	7067	0.6	
	30	C30	2-Cyl.	93→97	B8HS-10	5126	BR8HIX	7001	1.0	
	30	F30, F30A Dia. 12 mm plug	OHC 4-Stroke	01→05	DPR6EA-9	5531			0.9	
35 HP	35	35	3-Cyl.	87→97	B8HS-10	5126	BR8HIX	7001	1.0	
40 HP	40	40AE, 40AM, 40AR			B8HS	5510	BR8HIX	7001	0.6	
	40	40BE, 40BM, 40BR			B8HS	5510	BR8HIX	7001	0.6	
	40	40D, 40F		→89	B8HS	5510	BR8HIX	7001	0.6	
	40	40GK			B7HS	5110	BR7HIX	7067	0.6	
	40	40H			BR7HS-10	1098	BR7HIX	7067	1.0	
	40	40J		01→	B7HS	5110	BR7HIX	7067	0.6	
	40	40Q		95→	BR8HS	4322	BR8HIX	7001	0.6	
	40	40V		95→	BR7HS-10	1098	BR7HIX	7067	1.0	
	40	40X, E40X		→00	BR7HS	4122	BR7HIX	7067	0.6	
	40	40Y		04→07	BR8HS-10	1134	BR8HIX	7001	1.0	
	40	C40	2-Cyl.	89→97	B8HS	5110	BR8HIX	7001	0.6	
	40	C40	3-Cyl.	97→02	B7HS-10	2129	BR7HIX	7067	1.0	
	40	F40A	4-Cyl. 4-Stroke	99→	DPR6EA-9	5531			0.9	
	40	F40C			DPR5EA-9	2887			0.9	
40	F40B	3-Cyl. 4-Stroke	00→05	DPR6EA-9	5531			0.9		
45 HP	45	F45A/AETL			DPR6EA-9	5531			0.9	
48 HP	48	48A, 48B, E48		95→00	B7HS	5110	BR7HIX	7067	0.6	
50 HP	50	50		01→	B8HS-10	5126	BR8HIX	7001	1.0	
	50	50D		84→05	BR8HS-10	1134	BR8HIX	7001	1.0	
	50	50G, 50H		95→	BR8HS-10	1134	BR8HIX	7001	1.0	
	50	50TLRB		03→	B7HS-10	2129	BR7HIX	7067	1.0	
	50	C50		99→01	B8HS	5510	BR8HIX	7001	0.6	
	50	C50CE		98→	BR8HS-10	1134	BR8HIX	7001	1.0	
	50	F50	4-Cyl. 4-Stroke OHC EFI	05→	DPR6EB-9	3108			0.9	
	50	FT50B, FT50C	4-Cyl. 4-Stroke OHC	95→07	DPR6EA-9	5531			0.9	
	50	FT50G, FT50J	4-Cyl. 4-Stroke OHC EFI	05→21	DPR6EB-9	3108			0.9	
	50	P50	3-Cyl.	87→96	BR8HS-10	1134	BR8HIX	7001	1.0	
	55 HP	55	55AE		→78	B8HS	5510	BR8HIX	7001	0.6
55		55AE		79→	B8HS-10	5126	BR8HIX	7001	1.0	
55		55AEM, 55AM, 55AW			B8HS	5510	BR8HIX	7001	0.6	
55		55B		90→02	BR8HS-10	1134	BR8HIX	7001	1.0	
55		C55	2-Cyl.	89→95	B8HS-10	5126	BR8HIX	7001	1.0	
60 HP	60	60	2-Stroke	01→05	B8HS-10	5126	BR8HIX	7001	1.0	
	60	60AE		→78	B8HS	5510	BR8HIX	7001	0.6	
	60	60AE		79→	B8HS-10	5126	BR8HIX	7001	1.0	
	60	60B			B8HS-10	5126	BR8HIX	7001	1.0	
	60	60CE, 60CET		96→02	B8HS-10	5126	BR8HIX	7001	1.0	
	60	60D		86→	BR8HS-10	1134	BR8HIX	7001	1.0	
	60	60DE			B8HS-10	5126	BR8HIX	7001	1.0	
	60	60F			BR8HS-10	1134	BR8HIX	7001	1.0	
	60	E60H		95→00	B8HS-10	5126	BR8HIX	7001	1.0	
	60	FT60B	4-Stroke	03→06	DPR5EA-9	2887			0.9	
	60	FT60D, FT60G	4-Stroke EFI	05→21	DPR6EB-9	3108			0.9	
	60	P60	3-Cyl.	91→99	B8HS-10	5126	BR8HIX	7001	1.0	
	65 HP	65	65	3-Cyl.	87→97	B8HS-10	5126	BR8HIX	7001	1.0
	70 HP	70	70B		84→05	B8HS-10	5126	BR8HIX	7001	1.0
70		70ETO			BR8HS-10	1134	BR8HIX	7001	1.0	
70		C70		00→01	B8HS-10	5126	BR8HIX	7001	1.0	
70		F70AETL		10→	LKR7E	1643			0.9	
75 HP	75	75A, 75B			BR8HS-10	1134	BR8HIX	7001	1.0	
	75	C75, E75, P75		94→00	B8HS-10	5126	BR8HIX	7001	1.0	
	75	F75	4-Stroke	03→05	LF5AP-11	4775			1.1	
80 HP	80	80A			BR8HS-10	1134	BR8HIX	7001	1.0	
	80	C80	3-Cyl.	97→	B8HS-10	5126	BR8HIX	7001	1.0	



UPGRADE



MODEL	HP	ADDITIONAL INFORMATION	ENG TYPE E: = Eng no.	DATE	PART NO.	STOCK NO.	UPGRADE	STOCK NO.	GAP MM
YAMAHA (CONTINUED)									
80 HP	80	F80		99→02	LF5AP-11	4775			1.1
	80	F80A		06→	LF5A-11	6376	LF5AP-11	4775	1.1
85 HP	85	85A			BR8HS-10	1134	BR8HIX	7001	1.0
	85	C85		89→96	B8HS-10	5126	BR8HIX	7001	1.0
90 HP	90	90A		84→05	B8HS-10	5126	BR8HIX	7001	1.0
	90	B90, C90		97→01	B8HS-10	5126	BR8HIX	7001	1.0
100 HP	90	F90		03→05	LF5A-11	6376	LF5AP-11	4775	1.1
	100	100A		98→	BR8HS-10	1134	BR8HIX	7001	1.0
100 HP	100	F100		99→02	LF5A-11	6376	LF5AP-11	4775	1.1
	100	F100			4-Stroke				
115 HP	115	115A, 115E		84→87	B8HS-10	5126	BR8HIX	7001	1.0
	115	115B, 115C		88→13	BR8HS-10	1134	BR8HIX	7001	1.0
	115	B115, C115		98→99	BR8HS-10	1134	BR8HIX	7001	1.0
	115	F115A		00→15	LF6A-11	3672	ILFR6T11	4904	1.1
	115	F115B		14→	LKR6E	92650			0.9
	115	FL115A		00→15	LF6A-11	3672	ILFR6T11	4904	1.1
	115	FL115B		14→	LKR6E	92650			0.9
	115	P115, S115		84→05	BR8HS-10	1134	BR8HIX	7001	1.0
130 HP	130	130A, 130B		88→04	BR9HS-10	4551	BR9HIX	5687	1.0
	130	L130, S130		88→01	BR9HS-10	4551	BR9HIX	5687	1.0
140 HP	140	140A, 140B		→88	BR8HS-10	1134	BR8HIX	7001	1.0
	140	140B, 140C		89→	BR9HS-10	4551	BR9HIX	5687	1.0
	140	L140C		95→	BR9HS-10	4551	BR9HIX	5687	1.0
150 HP	150	150A		84→85	BR7HS-10	1098	BR7HIX	7067	1.0
	150	150A, 150C		86→02	BR8HS-10	1134	BR8HIX	7001	1.0
	150	150F, 150G		96→07	BR7HS-10	1098	BR7HIX	7067	1.0
	150	D150H		97→02	BR8HS-10	1134	BR8HIX	7001	1.0
	150	F150A, F150B		04→14	LF5A-11	6376	LF5AP-11	4775	1.1
	150	F150D, F150F		15→21	LF5A-11	6376	LF5AP-11	4775	1.1
	150	F150G		17→21	LF6A-11	3672	ILFR6T11	4904	1.1
	150	FL150A, FL150B, FL150D		04→21	LF5A-11	6376	LF5AP-11	4775	1.1
	150	FL150G		17→21	LF6A-11	3672	ILFR6T11	4904	1.1
	150	L150A		88→89	BR8HS-10	1134	BR8HIX	7001	1.0
	150	L150F		96→03	BR7HS-10	1098	BR7HIX	7067	1.0
	150	LZ150P		00→01	BKR6E-11	2756	BKR6EIX-11	3764	1.1
	150	LZ150P		02→07	BKR6EUK	6993	BKR6EIX	6418	X
	150	Z150P, Z150Q		00→01	BKR6E-11	2756	BKR6EIX-11	3764	1.1
	150	Z150P, Z150Q		02→07	BKR6EUK	6993	BKR6EIX	6418	X
175 HP	175	175A, 175B, 175D, 175F		84→03	BR8HS-10	1134	BR8HIX	7001	1.0
	175	F175A, F175B, F175C		14→21	LF6A-11	3672	ILFR6T11	4904	1.1
	175	FL175C		17→21	LF6A-11	3672	ILFR6T11	4904	1.1
	175	Z175G, Z175H		01→01	BKR7E-11	1283	IFR7G-11KS	7746	1.1
	175	Z175G		02→07	BKR7EUK	5881	BKR7EIX	2667	X
200 HP	200	200A, 200B, 200E, 200F, 200G (Excl. 200C)		85→10	BR8HS-10	1134	BR8HIX	7001	1.0
	200	200C		92→93	BR9HS-10	4551	BR9HIX	5687	1.0
	200	F200A		02→07	LF5A-11	6376	LF5AP-11	4775	1.1
	200	F200C, F200F, F200G		06→21	LF6A-11	3672	ILFR6T11	4904	1.1
	200	FL200A		02→07	LF5A-11	6376	LF5AP-11	4775	1.1
	200	FL200C, FL200F, FL200G		06→21	LF6A-11	3672	ILFR6T11	4904	1.1
	200	L200A, L200B, L200E, L200F		85→10	BR8HS-10	1134	BR8HIX	7001	1.0
	200	LZ200N		00→01	BKR7E-11	1283	IFR7G-11KS	7746	1.1
	200	LZ200N		02→05	BKR7EUK	5881	BKR7EIX	2667	X
	200	Pro V200		91→95	BR9HS-10	4551	BR9HIX	5687	1.0
	200	VZ200T		01→04	BKR7EUK	5881	BKR7EIX	2667	X
	200	Z200N		00→01	BKR7E-11	1283	IFR7G-11KS	7746	1.1
	200	Z200N, Z200P		02→07	BKR7EUK	5881	BKR7EIX	2667	X
	220 HP	220	220A		84→86	BR8HS-10	1134	BR8HIX	7001
225 HP	225	225C, 225D		94→09	BR8HS-10	1134	BR8HIX	7001	1.0
	225	F225A		02→07	LF5A-11	6376	LF5AP-11	4775	1.1
	225	F225B, F225C, F225F, F225H, F225J		07→21	LF6A-11	3672	ILFR6T11	4904	1.1
	225	FL225A		02→07	LF5A-11	6376	LF5AP-11	4775	1.1
	225	FL225B, FL225F, FL225H		07→21	LF6A-11	3672	ILFR6T11	4904	1.1
	225	L225C		94→95	BR8HS-10	1134	BR8HIX	7001	1.0
250 HP	250	250A, 250E, 250G		90→10	BR8HS-10	1134	BR8HIX	7001	1.0
	250	250B		97→03	BR9HS-10	4551	BR9HIX	5687	1.0
	250	F250A, F250B, F250D, F250L, F250N, F250P		06→21	LF6A-11	3672	ILFR6T11	4904	1.1
	250	FL250A, FL250B, FL250D, FL250L		06→21	LF6A-11	3672	ILFR6T11	4904	1.1
	250	L250A		90→06	BR8HS-10	1134	BR8HIX	7001	1.0
	250	L250B		97→03	BR9HS-10	4551	BR9HIX	5687	1.0
	250	L250G		06→10	BR8HS-10	1134	BR8HIX	7001	1.0
	250	LZ250D		03→07	BKR6EUK	6993	BKR6EIX	6418	X
	250	SL250A		97→97	BR8HS-10	1134	BR8HIX	7001	1.0
	250	Z250D, Z250F		03→07	BKR6EUK	6993	BKR6EIX	6418	X
300 HP	300	F300A, F300B, F300C, F300D, F300F, F300G		08→21	LF6A-11	3672	ILFR6T11	4904	1.1
	300	FL300A, FL300B, FL300C, FL300D		08→21	LF6A-11	3672	ILFR6T11	4904	1.1
	300	LZ300A		04→07	BKR6EUK	6993	BKR6EIX	6418	X
	300	Z300A		04→07	BKR6EUK	6993	BKR6EIX	6418	X
345 HP	345	F350A		08→	LF6A-11	3672	ILFR6T11	4904	1.1
BLASTER	-	WB700			BR8HS	4322	BR8HIX	7001	0.6
EXCEL	-			87→89	BR9HS-10	4551	BR9HIX	5687	1.0
FX1	-	FX700			BR8HS	4322	BR8HIX	7001	0.6
MJ500S/T	-				B7HS	5110	BR7HIX	7067	0.6
RAIDER	-	RA700, RA700A			BR8HS	4322	BR8HIX	7001	0.6
	-	RA1100			BR8HS	4322	BR8HIX	7001	0.6
RUNNER	-	RUNNER III, GP			BR8HS	4322	BR8HIX	7001	0.6
WRA650, WRA700	-				BR8HS	4322	BR8HIX	7001	0.6

**HP****UPGRADE**

MODEL	HP	ADDITIONAL INFORMATION	ENG TYPE E: = Eng no.	DATE	PART NO.	STOCK NO.	UPGRADE	STOCK NO.	GAP MM
YAMAHA (CONTINUED)									
SUPERJET	-	SJ650			BR8HS	4322	BR8HIX	7001	0.6
	-	SJ700			BR8HS	4322	BR8HIX	7001	0.6
VENTURE	-	WVT700			BR8HS	4322	BR8HIX	7001	0.6
VXR	-	WRB650			BR8HS	4322	BR8HIX	7001	0.6
WJ500/F (89)	-				B7HS	5110	BR7HIX	7067	0.6
WR500/F (89)	-				B7HS	5110	BR7HIX	7067	0.6
Z-DRIVE	-		Inline 4		BR6FS	4323			0.6
	-		V6		BR6FS	4323			0.6
	-		V8		BR6FS	4323			0.6
	-		V8		BR6FS	4323			0.6
	-		V8		BR6FS	4323			0.6

YAMATO									
MODELS	-	35			B6HS	4510	BR6HIX	3419	0.5
	-	350			B6HS	4510	BR6HIX	3419	0.5

ZÜNDAPP									
5 HP	5	5 CV			B6HS	4510	BR6HIX	3419	0.5
	5	Type 304			B6HS	4510	BR6HIX	3419	0.5
6 HP	6	Type 304			B6HS	4510	BR6HIX	3419	0.5
DELPHIN	-				B6HS	4510	BR6HIX	3419	0.5